



**Product Family**  
**Laser Lite Single-Use Earplug**







Highly visible protection

[Learn more about our products at howardleight.com](http://howardleight.com)

>



**Product Numbers & Ordering Information**

	Product Numbers	Details
	8015911	<b>LASER-LITE - BOX OF 10 PAIRES IN INDIVIDUAL BAG SNR 30 DB</b> Product emphasized in an effective packaging designed for a self-service environment.
	1015911	<b>LASER-LITE - BOX OF 10 PAIRES IN INDIVIDUAL BAG SNR 30 DB</b> Product emphasized in an effective packaging designed for a self-service environment.
	3301106	<b>Laser Lite - corded</b> SNR 35 H - 34 M - 32 L - 31
	3301105	<b>Laser Lite - uncorded</b> SNR 35 H - 34 M - 32 L - 31
	1013047	<b>Laser Lite - uncorded bulk refill for Leight Source 400</b> SNR 35 H - 34 M - 32 L - 31
	3301271	<b>Laser Lite - uncorded bulk refill for Leight Source 500</b> SNR 35 H - 34 M - 32 L - 31

**Overview**

**Key Features**

## Laser Lite Single-Use Earplug - EMEA1

- Vibrant colors make protection visible
- Self-adjusting polyurethane foam expands to fit virtually every wearer
- Contoured T-shape for easy insertion and wear
- Smooth, soil-resistant closed cell-foam skin prevents dirt build-up
- Available in paper bag packaging and/or with cotton cords for process industries [pulp & paper]
- Bulk refills for Leight Source 400 and Leight Source 500 Earplug Dispensers save time, waste and space

### Recommended Industries/Use

- Agriculture
- Chemical
- Construction
- Fire Protection
- Forestry
- Government
- Law Enforcement
- Manufacturing
- Medical
- Military
- Mining
- Municipal Services
- Oil and Gas
- Pharmaceutical
- Steel and Metals
- Transportation
- Utilities
- Welding

### Hazards

- Noise

### Regulations

- 29 CFR 1910.95 - 29 CFR 1910.95
- S3.19-1974 - Attenuation Test Protocol (US)
- Part II, (R.S.C. 1985, c. L-2) - Canada Labour Code
- Z94.2-1994 - Attenuation Test Protocol (CAN)
- 2003/10/EC - EU Hearing Directive
- 89/686/EEC - EU Directive/PPE
- Category II - EC Category/PPE
- EN 352-2:1993 - EU Standards
- EN-24869-1:1993 - EU Standards
- NOHSC: 1007 (2000) - National Standard for Occupational Noise (AUS/NZ)
- NR 15 - Security and Health of Work, Annexes 1 and 2, n°3.214/1978 - Occupational Noise Regulations (BR)
- ANSI S12.6/1997 - Method B - Attenuation Test Protocol (BR)
- 9001:2008 - ISO

### Historical Brand

Howard Leight

## Specifications

### Color

- Magenta/Yellow

### Shape

- T-Shape

### Material

- Polyurethane Foam

### Packaging Options

- • Polybag • Paper Bag • Bulk Refill for Leight Source 400 or Leight Source 500 Dispenser

### Cord Options

- • Uncorded • Polycord • Cotton Cord

### NRR

- 32

### Canada Class

- A(L)

### SNR

- 35

### SLC80

- 25 dB / Class 4

EU Certifications

- European Directives – 89/686/EEC
- EC Category PPE – Category II
- Standards – EN 352-2:1993 / EN-24869-1:1993
- EC Certification Number – 951095
- EC Attestation Number – 9503632
- Laboratory – B.G.I.A.

AUS Certifications

- Standardsmark License #1579

**Certifications**

**EU Certificate - Laser Lite**

[http://www.honeywellsafety.com/Supplementary/Documents\\_and\\_Downloads/Secured/Hearing\\_Protection/Earplugs/20035/1033.aspx](http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Secured/Hearing_Protection/Earplugs/20035/1033.aspx)

EU Certificate - Laser Lite

**EU Certificate - Earplugs**

[http://www.honeywellsafety.com/Supplementary/Documents\\_and\\_Downloads/Secured/Hearing\\_Protection/Earplugs/42685/1033.aspx](http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Secured/Hearing_Protection/Earplugs/42685/1033.aspx)

EC Declaration of conformity The manufacturer SPERIAN HEARING PROTECTION, LLC, 7828 Waterville Rd. San Diego, CA 92154 United States declares that the Personal Protective Equipment (PPE) items listed below, conform with the provisions of Council Directive 89/686/EEC and, where applicable, with the national standard, tr

**EU Certification Report - Laser Lite**

[http://www.honeywellsafety.com/Supplementary/Documents\\_and\\_Downloads/Secured/Hearing\\_Protection/Earplugs/20049/1033.aspx](http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Secured/Hearing_Protection/Earplugs/20049/1033.aspx)

EU Certification Report - Laser Lite

**Literature & Documents**

**Instruction Manual - Laser Lite (global)**

[http://www.honeywellsafety.com/Supplementary/Documents\\_and\\_Downloads/Hearing\\_Protection/Earplugs/4294986713/1033.aspx](http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/4294986713/1033.aspx)

**Earplug Instruction Poster - EN**

[http://www.honeywellsafety.com/Supplementary/Documents\\_and\\_Downloads/Hearing\\_Protection/Earplugs/19799/1033.aspx](http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/19799/1033.aspx)

**Training & Proper Use**

1. With clean hands, roll the entire earplug into narrowest possible crease-free cylinder.
2. Reach over your head with a free hand, pull your ear up and back, and insert the earplug well inside your ear canal.
3. Hold for 30 – 40 seconds, until the earplug fully expands in your ear canal. If properly fitted, the end of the earplugs should not be visible to someone looking at you from the front.
4. Proper Fit – If either or both earplugs do not seem to be fitted properly, remove the earplug and reinsert
5. Removal – Gently twist earplug while slowly pulling in an outward motion for removal.
6. Acoustical Check – In a noisy environment, with earplugs inserted, cup your hands over your ears and release. Earplugs should block enough noise so that covering your ears with your hands should not result in a significant noise difference.

## Additional Information

### CARE + MAINTENANCE

- **INSPECT** – Inspect prior to fitting, examine your earplugs for dirt, damage or extreme hardness—discard immediately if compromised.
- **DISCARD** – For proper hygiene, discard Single-Use earplugs after use.
- **HYGIENE** – To maintain hygiene standards, Single-Use earplugs should be discarded at the end of every shift.